# **WISE-4471**

## Cat. NB1/ Cat. M1 Wireless I/O Module



## W C E FC IC

## Introduction

NB-IoT and LTE Cat M1 are new wireless technologies included in the 5G evolution of cellular technology standards defined by the 3rd Generation Partnership Project (3GPP). NB-IoT and LTE Cat M1 feature low power consumption and utilize LTE networks based on licensed spectrum bands. These technologies are optimized for connectivity to machines, assets and sensors in order to enable IoT applications such as smart cities, smart agriculture and remote asset management.

WISE-4471 series is a 4G cellular based IoT wireless sensor node compliant with LTE Cat. NB1 and Cat. M1 with built in antenna for flexible installation. In addition to offering various I/O types, WISE-4471 series provides a data logger and direct cloud connectivity so that data can be published to the cloud by messaging protocol such as MQTT, CoAP, LwM2M with secure socket supported.

#### **Features**

#### **Automatic Connection with Cloud**

By utilizing leading IoT messaging protocols such as MQTT and CoAP, WISE-4671 series easily integrates with popular cloud services, reducing setup complexity and accelerating implementation.



#### **Open Connectivity for Cloud and System**

WISE-4471 series support CoAP and MQTT communication protocols while continually integrating mainstream cloud services to simplify the complexity of data integration.



### **Features**

- Global coverage of Cat. NB1 and Cat. M1 frequency bands
- Application-ready I/O combination with optional IP65 I/O
- Wide voltage power input with 10 ~ 50V<sub>DC</sub>
- Data buffered function with time stamp reducing data lost
- · Fast and easy deployment to reduce operation cost
- Supports direct cloud service for IoT integration
- Support MQTT, CoAP & LwM2M protocol

#### **Legacy and Existing Devices to NB-IoT/eMTC**

WISE-4471 series offer digital I/O, 4~20-mA analog and RS-232/485 interfaces for various applications, quickly providing NB-IoT/eMTC network functions to existing devices and assets.



#### **Upgrade Legacy Equipment though Cloud Management**

WISE-4471 series NB-IoT/eMTC sensor nodes are suitable for data collection from widely distributed assets. No complicated programming, setup, or registration are required for a fast introduction into IoT applications such as smart cities, smart water/electricity meters, and remote facility management.



#### **Device to Cloud System Architecture**

WISE-4471 series wireless sensor nodes support the open communication protocols MQTT, CoAP, and LwM2M. Users can transmit data to specific public cloud services or existing private cloud platforms by publish/subscribe or push.





# **Specification**

#### **Wireless Communication**

3GPP Standards R.13, Cat. NB1/ Cat. M1 2, 3, 4, 5, 8, 12, 13, 20, 28 Frequency Band Antenna Type Internal

#### General

Power Input 10 ~ 50Vpc external power Power Consumption 2 0 W 2.0 W Micro-B USB 3FF/Micro SIM Configuration Interface SIM

Connector WISE-4471-S2xx: WISE-4471-S4xx: Plug-in screw terminal block (I/O and power) M12 4-pin code-A male x 1 (Power) M12 8-pin code-D female x 1 (I/O) Status, Error, Tx, Rx, Signal Level LED Indicator

Mounting
Dimension (W x H x D)
Certification DIN 35 rail, wall, pole and stack 70 x 112 x 38 mm CE, NCC, FCC, IC

## WISE-S214 (4AI/4DI)

#### **Analog Input**

Channels Sampling Rate

4 16bits Bipolar; 15bits Unipolar 10Hz (Total) with50/60Hz Rejection ±0.1% for Voltage Input; ±0.2% for Current Input 0-150mV, 0-500mV, 0-1V, 0-5V, 0-10V, ±150mV, ±500mV, ±1V, ±5V, Accuracy Input Range

 $\pm 10$ V, 0~20mA,  $\pm 20$ mA, 4-20mA >1M $\Omega$  (Voltage) 240  $\Omega$  (External resistor for current) ■ Input Impedance ■ Support Data Scaling and Averaging

#### **Digital Input**

Channels 4 (Dry Contact)

Compatibility 3.3V/TTL
Supports 200Hz Counter Input (32-bit + 1-bit overflow)

Supports keep/discard counter value on power-off Support inverted digital input status

# WISE-S250 (6DI, 2D0& 1RS-485)

#### **Digital Input**

 Channels
 Compatibility
 Supports 3kHz Frequency Input 6 (Dry Contact) 3.3V/TTI

#### **Digital Output (Sink Type)**

Channel Output Current 2 100 mA At 0 -> 1: 100 us At 1 -> 0: 100 us (for Resistive Load) Supports Pules Output Max. Load Voltage 5 kHz

#### **Serial Port**

Port Number RS-485 Type Data Bits 7, 8 1, 2 Stop Bits Parity Baud Rate (bps) None, Odd, Even

1200, 2400, 4800, 9600, 19200, 38400, 57600, 115200 Modbus/RTU (Total 64 addresses by 30 max. instructions)

## WISE-S251 (6DI/1RS-485)

#### **Digital Input**

Channels Compatibility 6 (Dry Contact) 3.3V/TTL Supports 200Hz Counter Input (32-bit +1-bit overflow)
Supports keep/discard counter value on power-off
Support inverted digital input status

# **Serial Port**

Port Number RS-485 Stop Bits

Parity Baud Rate (bps)

None, Odd, Even 1200, 2400, 4800, 9600, 19200, 38400, 57600, 115200 Modbus/RTU (Total 64 address by max. 20 instructions)

# **Ordering Information**

■ WISE-4471-UA Cat. NB1/Cat. M1 Wireless Module

#### WISE-S200 I/O Module

WISE-S214-A WISE-S250-A 4AI/4DI 6DI, 2DO & 1RS-485 6DI & 1RS-485 WISE-S251-A


#### **Accessories**

DIN Rail Power Supply (1.25A Output Current)
Power Supply, 12V/1A, US plug
Power Supply, 12V/1A, EU plug
M12 Connector 8P Male
M12 Connector 4P Female
2M M12 code-A 4-pin female cable for power wiring
2M M12 code-D 8-pin male cable for I/O wiring 96PSD-A30W24-DS BB-RPS-V2-WR2-US BB-RPS-V2-WR2-EU

1655005903-01


1700028162-01 1700028163-01

# **Dimensions**



Front View Side View





Unit: mm